


## NASA TECHNICAL NOTE

NASA TN D-2216  
C-1

NASA TN D-2216

LOAN COPY: RETD  
AFWL (WLIL-  
KIRTLAND AFB, NON FREQUENCY MEASUREMENTS  
AND RESOLUTION

*by Alan M. Demmerle*  
*Goddard Space Flight Center*  
*Greenbelt, Md.*

NATIONAL AERONAUTICS AND SPACE ADMINISTRATION • WASHINGTON, D. C. • DECEMBER 1964





# ON FREQUENCY MEASUREMENTS AND RESOLUTION

By Alan M. Demmerle

Goddard Space Flight Center  
Greenbelt, Md.

NATIONAL AERONAUTICS AND SPACE ADMINISTRATION

---

For sale by the Office of Technical Services, Department of Commerce,  
Washington, D.C. 20230 -- Price \$0.50

# **ON FREQUENCY MEASUREMENTS AND RESOLUTION**

by

Alan M. Demmerle

*Goddard Space Flight Center*

## **SUMMARY**

This article relates the resolution to which the frequency of a sine wave can be measured (using zero-crossing techniques) to the signal-to-noise ratio of the wave and the time available to make the wave measurement. It demonstrates the need for making measurements over a constant time interval, instead of a constant number of cycles, if the resolution of measurement is to be independent of frequency.



## CONTENTS

Summary . . . . .	i
INTRODUCTION . . . . .	1
RELATION BETWEEN RESOLUTION AND NOISE . . . . .	1
CONCLUSIONS . . . . .	6

# ON FREQUENCY MEASUREMENTS AND RESOLUTION

by

Alan M. Demmerle

*Goddard Space Flight Center*

## INTRODUCTION

The resolution to which the frequency of a sine wave perturbed by noise can be measured, by zero-crossing counting techniques, is related to the signal-to-noise ratio (S/N), the length of time over which the measurement is made, and the frequency to be measured. Familiarization with these relations facilitates the optimum use of the measurement technique.

The resolution of the measurement may be defined in a number of ways. The frequency to be measured is known to within two bounds,  $f_{\max}$  and  $f_{\min}$ . If this range is divided into  $100/m$  equal increments, and the measurement is able to distinguish only between one of these increments and its neighbors, then the measurement of  $f$  is said to be *resolved* to  $m$  percent.

## RELATION BETWEEN RESOLUTION AND NOISE

Noise fluctuations added to a sine wave of voltage affect the measurement of the frequency of that voltage. If the frequency is measured by zero-crossing techniques, the effects of the noise on the measurement can be determined under two assumptions. The first is that only  $2n + 1$  zero crossings are detected per  $n$  cycles. The second assumption is that the perturbing additive noise has a Gaussian distribution. Let

$e = a \sin 2\pi ft$  = the input signal when it is free of noise,

$m \triangleq$  resolution, in percent of full scale, to which the measurement must be made,

$f \triangleq$  the frequency to be resolved to  $m$  percent of its total possible range  $B$ ,

$B \triangleq f_{\max} - f_{\min}$  (See Figure 1),

$c \triangleq \frac{mB}{100}$  = the number of cps between resolvable elements,

$n \triangleq$  the number of cycles over which a measurement is made.

Since there are  $c$  cps between resolvable elements, the measurement is to determine if the frequency is  $f_1$ , its neighbor  $f_2$  which equals  $f_1 + c$ , or its other neighbor  $f_3$  which equals  $f_1 - c$ .




Figure 1—The frequency, as constrained within a specified range B.




Figure 2—Determination of frequency by measurement of the elapsed time per cycle.

Frequency is determined by measuring the elapsed time per cycle (Figure 2). The time measurement  $t_1$  of one frequency  $f_1$  and the time measurement  $t_2$  of its neighboring resolvable frequency  $f_2$  differ by  $1/f_1 - 1/f_2$ . In general the magnitude of the difference in a 1 cycle time measurement between two adjacent resolvable elements of frequency is

$$\Delta t|_{n=1} = \frac{1}{f} - \frac{1}{f+c} \text{ or } -\frac{1}{f} + \frac{1}{f-c} \quad (1)$$

In order to resolve the measurement of frequency to  $c$  cps, i.e., discriminate between  $f$  and its neighboring frequency  $f+c$  or  $f-c$ , the measurement of elapsed time for 1 cycle must be in error by no more than  $|\Delta t|_{n=1}$ . If the measurement is to be made over  $n$  cycles, the required resolution can be maintained with  $n$  times the time measurement error for 1 cycle.

The magnitude of the total allowable time measurement error is (the neighbor  $f+c$  is used in this example),

$$\Delta T = n \left( \frac{1}{f} - \frac{1}{f+c} \right) \quad (2)$$

An approximation for the voltage error corresponding to a time error of  $\Delta T$  is (see Figure 3):

$$\Delta V = \Delta T \left. \frac{de}{dt} \right|_{t=0} = \Delta T (2\pi f a) \quad (3)$$

$$|\Delta V| = 2\pi f n a \left( \frac{1}{f} - \frac{1}{f+c} \right) \quad (4)$$

The validity of this approximation depends on a relatively large  $S/N$ . This error could be caused either by a measurement error due to the measurement instrument itself or by noise which is perturbing the input signal. The analysis here neglects the instrument error.

These measurement errors, because they are due to random noise, are themselves random processes, and therefore must be considered from a statistical point of view. We shall consider  $\Delta T$  and  $\Delta V$  to be no longer distinct and constant, but rather random variables which can assume,

any value and have associated with them a probability density distribution.

The error  $\Delta T$ , and hence  $\Delta V$ , is an algebraic summation of the errors due to noise from two measurements, the measurements of time at the first zero-crossing and at the zero-crossing at the end of  $n$  cycles. Therefore, by assuming a stationary process and a statistical independence between the readings, the standard deviation of one measurement and the algebraic sum of the two measurements are related by

$$\sigma(\text{sum}) = \sqrt{2} \sigma(\text{one}), \quad (5)$$

where  $\sigma(\text{sum})$  is the standard deviation of  $\Delta V$  in Equation 4 and  $\sigma(\text{one})$  is the rms voltage of the additive Gaussian noise which is causing the error in each measurement.

When a resolution  $c$  is prescribed for the measurement, the percentage of measurements that fall within  $c$  must also be prescribed. The probability (or percentage of measurements) that the time error  $\Delta T$  will be found within  $\pm K\sigma$  of its mean (which is zero) can be written in terms of the error function

$$\text{erf}\left(\frac{K}{\sqrt{2}}\right) \triangleq \frac{2}{\sqrt{\pi}} \int_0^{K/\sqrt{2}} e^{-v^2} dv, \quad (6)$$

where  $\text{erf}(K/\sqrt{2}) = \text{Probability } (-K\sigma < \Delta T < K\sigma)$  and  $v \triangleq$  a dummy variable. The function  $1 - \text{erf}(K/\sqrt{2})$  is plotted vs.  $K$  on Figure 4.

Combining the notions of Equations 4-6 gives

$$\begin{aligned} \Delta V &= K\sigma(\text{sum}) = \sqrt{2} K\sigma(\text{noise}), \\ \sigma(\text{noise}) &= \frac{\Delta V}{K\sqrt{2}} = \frac{2\pi fna}{K\sqrt{2}} \left( \frac{1}{f} - \frac{1}{f+c} \right), \\ \left( \frac{S}{N} \right)_{\text{rms voltage}} &= \frac{\frac{a}{\sqrt{2}}}{\sigma(\text{noise})} = \frac{\frac{a}{\sqrt{2}}}{\frac{2\pi fna}{K\sqrt{2}} \left( \frac{1}{f} - \frac{1}{f+c} \right)}, \\ \left( \frac{S}{N} \right)_{\text{rms voltage}} &= \frac{K}{2\pi fn \left( \frac{1}{f} - \frac{1}{f+c} \right)}, \end{aligned} \quad (8)$$




Figure 3—Signal voltage error displacement as a function of the time error displacement.



$$\frac{S}{N} \text{ (db)} = 20 \log \left[ \frac{0.159K}{n \left( 1 - \frac{f}{f+c} \right)} \right].$$

Equation 8 is plotted in its logarithmic form on Figure 5. Rewriting Equation 8 yields

$$c = f \left( \frac{1}{1 - \frac{K}{2\pi n \frac{S}{N}}} - 1 \right). \quad (9)$$

Note that with this technique, whereby a prespecified constant number of cycles is measured, the resolution to which the measurement can be made depends on the frequency of the input signal. This dependence can be changed by making the measurement over a constant interval of time  $T$  regardless of the frequency, where  $T = n/f$ . Substituting  $fT$  for  $n$  in Equation 8 yields:

$$\frac{S}{N} = \frac{K}{2\pi T} \frac{f+c}{cf}, \quad (10)$$

$$\frac{S}{N} \text{ (db)} = 20 \log \left( \frac{0.159K}{T} \frac{f+c}{cf} \right),$$

or

$$c = \frac{1}{\frac{S}{N} \frac{2\pi T}{K} - \frac{1}{f}}. \quad (11)$$

Equation 10 is plotted in its logarithmic form on Figure 6. Equation 11 is plotted on Figure 7. Note that with this method of measurement the resolution  $c$  is nearly independent of frequency when  $f$  is large compared with  $c$ , or the  $S/N$  required to make a measurement of specified resolution  $c$  is independent of frequency when  $f$  is large compared with  $c$ .




Figure 4—The error function ( $K$  vs  $1 - \text{erf } K/\sqrt{2}$ ).




Figure 5—The relation between  $S/N$  and frequency for a constant  $c$ ,  $n$ , and  $K$ .




Figure 6—The relation between  $S/N$  and frequency for a constant  $c$ ,  $T$ , and  $K$ .

Figure 6 (Equation 10) can serve the following purpose. Given (1) the resolution required of a measurement ( $c$  or  $m$ ), (2) the probability that a measurement must fall within the required resolution (thus, from Figure 4 deduce  $\kappa$ ), (3) the relative magnitude of the frequency  $f$ , and (4) the time available  $T$  to make the measurement, then the input  $S/N$  required can be determined. Figure 7 (Equation 11) can serve to determine the resolution  $c$  which can be obtained given the order of magnitude  $f$ , the probability that the measurement will be within the specified resolution (thus, from Figure 4 deduce  $\kappa$ ), the amount of time available to make the measurement ( $T$ ), and the  $S/N$ .

To show the relation between the required  $S/N$  and the probability that the measurements will be within the specified resolution  $c$ , Figure 8 was constructed. In determining this curve the variable  $K$  (the number of standard deviations chosen) was transformed to the probability parameter by the use of Figure 4. It is thus apparent that in order to keep the resolution to which a measurement can be made independent of frequency\* for a given  $S/N$ , the zero-crossing measurements must be made over a constant interval of time. The heuristic reason for this is that the total energy utilized in making the measurement is made independent of frequency.

In the case where the measurement is made by determining the elapsed time for  $n$  cycles,

\* For realistic values of  $c/f$ ; i.e.,  $f > 10c$ .




Figure 7—The relation between resolution and frequency for a constant  $S/N$ ,  $T$ , and  $K$ .




Figure 8—The relation between  $S/N$  and the probability that a measurement is resolved to better than  $c$  for a constant  $c$ ,  $T$ , and  $f$ .

independent of the frequency, the energy utilized in making the measurement is an inverse function of frequency. Hence for a constant S/N the resolution is dependent upon the frequency. Laboratory tests have demonstrated the correctness of Equation 10.\*

## CONCLUSIONS

When measurements of noisy sine waves are made by zero-crossing techniques, a constant resolution of measurement over all frequencies where  $f > 10 c$  can be made only by measuring for a constant length of time for all these frequencies.

It is possible, by the use of Equations 10 and 11 to compute (1) the required S/N for a specified resolution  $c$ , measured time  $T$ , and error function argument  $K$ , and (2) the possible  $c$  for a specified S/N,  $f$ ,  $T$ , and  $K$ .

(Manuscript received June 29, 1964)

\*Demmerle, A. M., and Heffner, P., "The Resolution of Frequency Measurements in PFM Telemetry," NASA Technical Note D-2217, 1964.

2/7/85  
6

*"The aeronautical and space activities of the United States shall be conducted so as to contribute . . . to the expansion of human knowledge of phenomena in the atmosphere and space. The Administration shall provide for the widest practicable and appropriate dissemination of information concerning its activities and the results thereof."*

—NATIONAL AERONAUTICS AND SPACE ACT OF 1958

## NASA SCIENTIFIC AND TECHNICAL PUBLICATIONS

**TECHNICAL REPORTS:** Scientific and technical information considered important, complete, and a lasting contribution to existing knowledge.

**TECHNICAL NOTES:** Information less broad in scope but nevertheless of importance as a contribution to existing knowledge.

**TECHNICAL MEMORANDUMS:** Information receiving limited distribution because of preliminary data, security classification, or other reasons.

**CONTRACTOR REPORTS:** Technical information generated in connection with a NASA contract or grant and released under NASA auspices.

**TECHNICAL TRANSLATIONS:** Information published in a foreign language considered to merit NASA distribution in English.

**TECHNICAL REPRINTS:** Information derived from NASA activities and initially published in the form of journal articles.

**SPECIAL PUBLICATIONS:** Information derived from or of value to NASA activities but not necessarily reporting the results of individual NASA-programmed scientific efforts. Publications include conference proceedings, monographs, data compilations, handbooks, sourcebooks, and special bibliographies.

*Details on the availability of these publications may be obtained from:*

SCIENTIFIC AND TECHNICAL INFORMATION DIVISION  
NATIONAL AERONAUTICS AND SPACE ADMINISTRATION  
Washington, D.C. 20546